

Power Cord

SC501-32HCHC-6-□M
32A 6mm² 3C IEC53 RVV Cable
SC501-32HCHC-4KYJV-□M
32A 4mm² 3C KYJV XLPE Cable



SC501-AUS-□M
• For Australia and China.
• Extension cord plug with rear socket.



SC502-CHTHRU-□M
• For Australia and China.
• Extension cord plug with rear socket.



SC501-32CEEHC-6-□M
32A 6mm² 3C IEC53 RVV Cable
SC501-32CEEHC-4KYJV-□M
32A 4mm² 3C KYJV XLPE Cable



SC501-US-□M



SC501-US-□M

SC501-UK-□M



SC501-UK-□M

SC501-AUS-□M



SC501-AUS-□M

SC501-CH-□M



SC501-CH-□M

SC501-EU-□M



SC501-EU-□M

SC501-FWMI-□M



SC501-FWMI-□M

SC501-FWFB-□M



SC501-FWFB-□M

SC501-592-□M



SC501-592-□M

SC501-BB-□M



SC501-BB-□M

DMX Adaptor



SVP559-3F5M
Female XLR 3P
to Male XLR 5P

SVP559-5F3M
Female XLR 5P
to Male XLR 3P


SVP557-5
Female XLR 5P
to Female XLR 5P

SVP558-5
Male XLR 5P
to Male XLR 5P


SC7102S-DMX
0.2m, Male XLR 5P to Female XLR 3P*2
• For Avolites console output.



SVP559-3F5M
SVP559-5F3M



SVP557-5
SVP558-5




110ohm DMX Terminator

SVP555S-BK-3P110
Male XLR 3P

SVP555S-BK-5P110
Male XLR 5P

SVP558-35-110
Male XLR 3, 5P
• For light system close loop.



Power Cord Item No. Rule:

① - ② ③ - ④ ⑤ - ⑥

	Remark	Define			
①	SC501	Power Cord			
②	32	32 AMP			
③		Power Connector Type			
④	(Default)	1.5	15	mm ²	AWG
	0.75	0.75	18		
	1	1	17		
	2	2	14		
	2.5	2.5	13		
	4	4	11		
⑤	(Default)	IEC53 RVV Cable			
	KYJV	KYJV XLPE Cable			
⑥		Length			

Example:

SC501 - 32 CEEHC - 4 KYJV - 20M

③ Power Connector Type Remark

HCHC: SVP592HC to SVP592HC
CEEHC: CEE Male 3P to SVP592HC
US: US IEC to SVP592-FA-BL
UK: UK to SVP592-FA-BL
AUS: AUS to SVP592-FA-BL
CH: China to SVP592-FA-BL
EU: EU to SVP592-FA-BL
FWMI: SVP598F-W to SVP598M-I
FWFB: SVP598F-W to SVP592-FB-GY
592: SVP592-FA-BL to SVP592-FB-GY
BB: SVP592-FA-BL to SVP592-FA-BL