Stage Box with Multi-Cable

SVP555V SVP556V

24CH, 20 XLR Input + 4 XLR Return
SBC-24X-TB-□FT
- Aluminum alloy cable grip.
- "MULTI CON" fantail stopper.
- Channel with plastic tubes and number tubes.

※ Flat Side Panel Item No.: SBC-2T-8F-RW-10M
※ Box XLR Socket Type: SVP561P-S-3.5
※ Fantail XLR Type: SVP555SC-BK with rainbow plastic cap.

SGB-2TH Box with L Type Handle
SBC-2TH-8F-RW-10M
- Nylon plastic cable gland.
- 8CH rainbow multi-cable, 10m.
- Box female XLR to fantail male XLR.

20CH, 16 XLR Input + 4 TRS Return
SBC-20T-P-□FT
- Nylon plastic cable gland.

Item No. Rule:

①	-	②	③	④	⑤	-	⑥
SBC	-	24	XVXBG	8	-TB	-	100FT

Example

	Remark	Define	
①	SBC	Stage Box with Multi-Cable	
②		Number of Channels (Include Return)	
③		Connector Type	
④	(Default)	Return	4 Return
	8		8 Return
⑤	(Default)	Box to Fantail	Aluminum Alloy Cable Grip (With XLR color mark ring remark: R34)
	-P		Nylon Plastic Cable Gland (With XLR color mark ring remark: -PR34)
	-TB		Aluminum Alloy Cable Grip, "MULTI CON" Fantail Stopper, Channel with Plastic Tubes and Number Tubes
⑥		Length: FT/M	

③ Connector Type

Remark	Input		Return	
	Stage Box Female XLR	Fantail Male XLR	Stage Box Male XLR	Fantail Female XLR
X	SVP561N	SVP555S	SVP555A-N	SVP556S
XV	SVP561N	SVP555V	SVP555A-N	SVP556V
XVP	SVP561P-S-3.5	SVP555V	SVP555P-3.5	SVP556V
XQYP	SVP561P-S-3.5	SVP555X-Q-GY	SVP555P-3.5	SVP556X-Q-GY
XVX	SVP561NX	SVP555V	SVP555AX	SVP556V
XVXBG	SVP561NX-BK-PG	SVP555V-BK-PG	SVP555AX-BK-PG	SVP556V-BK-PG
T	SVP561N	SVP555S	**TRS Phone Socket SJ246D**	**TRS Phone Plug SP101-CP2**
TV	SVP561N	SVP555V		
TVP	SVP561P-S-3.5	SVP555V		SVP556V
TVX	SVP561NX	SVP555V		SVP556V

④ Return Channel

4 Return		8 Return	
Channel	Input	Channel	Input
8	8	---	---
12	8	----	---
16	12	16	8
20	16	20	12
24	20	24	16
28	24	28	20
32	28	32	24
36	32	36	28
40	36	40	32

Aluminum Alloy Cable Grip

XLR Color Mark Ring 1CE0034
※ Only for SVP555S/SVP556S.

"MULTI CON" Fantail Stopper
※8 channels a group.

Channel with Heart-shrink PVC Plastic Transparent Tubes and Number Tubes

Nylon Plastic Cable Gland